

HOW TO SET UP THE 30001505DEU TO WORK WITH THE DEMO GUI

USER GUIDE



Description

This document will guide you through an example setup of the hardware and the LoRaModem GUI.



Contents

1.	Ov	erview	3
2.	На	rdware setup	3
2	.1.	Example of connection with USB to serial cable	4
3.	Sof	ftware setup	5
3	.1.	Starting the GUI	5
3	.2.	Module reset	6
	Cor	mmand example	7
4.	Ser	nding and receiving a message	7
	Cor	mmand example	8
5.	Usi	ing AES ciphering	8
	Cor	mmand example	9
6.	Rev	vision History1	0



1. Overview

The LoRa modem module will be controlled by a PC software connecting via the serial port. The device will exchange some messages with a similar device.

The required material is:

- 2 x 30001505DEU DevKit mounting a 32001505DEU
- 2 x USB to UART 3v3 adapter (e.g.: FTDI TTL-232R-3V3)
- Power supply
- Mipot LoRaModem GUI

2. Hardware setup

The minimal connection with a host device uses the lines indicated in the following image and are comprised of the following pin:





PIN NAME	DIR	DESC
LPUART_TX	Out	UART TX pin, connect to RX pin of the adapter
LPUART_RX	In	UART RX pin, connect to TX pin of the adapter
NDATA_INDICATE	Out	Goes low when the module has data to send on the serial
NWAKE	In	Pull down to wake up the module from sleep.
VDD	Pwr	2.1 V to 3.6 V
GND	Pwr	Ground pin

2.1. Example of connection with USB to serial cable



The NWAKE pin is connected to the RTS signal. The Mipot LoRaModem GUI pull down the signal to wake up the module before sending data.



3. Software setup

3.1. Starting the GUI

Once all connections are made and the module are powered, start the LoRaModem GUI. At startup, it will scan available serial ports looking for connected devices. It is possible to connect multiple devices to the same PC.

🚺 LoRa Modem	- 🗆 X
File Help	
Module Tree NB-2401000419 COM39 COM38 COM33 COM42	Log Viewer 11:47:10 VRB "COM33": 1x -> "AA-34-00-22" : "?4\u0000"" 11:47:11 DBG "COM33": 1x -> "AA-B4-04-02-00-00-00-9C" : "??\u0004\u0002\u0008\u0000 u0000?" 11:47:11 VRB "COM33": 1x -> "AA-35-00-21" : "?5\u0000!" 11:47:11 DBG "COM33": 1x -> "AA-35-00-9C" : "??\u0004?\r\u0008\u0000?" 11:47:11 DBG "COM33": 1x -> "AA-35-00-9C" : "??\u0004?\r\u0008\u0000?" 11:47:21 VRB OnReadCommandClick 11:47:21 VRB "COM42": 1x -> "AA-33-02-00-05-1C" : "?3\u00002\u0000\u0005\u0001C" 11:47:21 VRB "COM42": 1x -> "AA-33-02-00-05-1C" : "?3\u00002\u0000\u0005\u0001C"
	<pre>11:47:21 DBG "COM42": A <- "AA-B3-06-08-02-08-04-01-82" : "??(u0005(u00))))))))))</pre>
	11:49:26 DBG "COM33": = <- "AA-D0-01-00-85": "??\u0001\u0000?" 11:49:27 DBG "COM33": = <- "AA-52-05-00-CF-00-00-00-30": "?R\u0005\u0000?\u0000 \u0000\u00000" 11:49:27 DBG "COM42": = <- "AA-53-07-00-F6-FF-0A-00-11-22-CA": "?S\u0007\u0000?? \n\u0000\u0001"?"

Once the scan is finished, the serial ports with the module connected will be highlighted in green. To use one of the module, double click on the appropriate Com port.

JRA Modem Module Selected Selected port COM33 Baud rate: (bp) pen					-		
Module Selected Selected port: COM33 Baid: configuration Device Information AES Configuration Project 9600 bps * Period Physic Parameters Data Indicate Time (ms): Baud Rate (bps): AES Enable (): AES Cryptography Write Factory Reset Selected Selected Selected Selected ABid: Configuration Provide Parameters Data Indicate Time (ms): Baud Rate (bps): AES Enable (): AES Cryptography Virte Selected Selected Selected Selected Selected Module Parameters Data Indicate Time (ms): Baud Rate (bps): AES Cryptography Module Selected Selected Selected	oRa Modem	1					
Selected port COM33 Baud rate: Ibps 9600 bps v Ten see Ten see Ten see Ten see Ten see Ten see Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See Ten See See See See See See See S	Module Selected	Radio Configuration	Davisa Information	AES Configuration	Transmission	Testing	
Bad rate: (bp:) 900 bps pen power (dBm) power (dBm) v Serial log viewer Power (DH) [13:47:11.186] COH33 Power (dBm) Power (dBm) Power (dBm) v Power (dBm)	Selected port: COM33	Radio Configuration	Device information	ALS CONIGUIATION	Industriission	resung	
See	Baud rate: (bps) 9600 bps Y	Physic Parameters					
See Frequency Band (MHz): See Write Bandwidth (KHz): Write Spreading Factor (chips): V Code Rate (): V Module Parameters Data Indicate Time (ms): Baud Rate (bps): AES Cryptography AES Enable (): EEPROM Factory Reset	bade fate. (ops) 5000 ops	Power (dBm)			~	Read	
ose Vite Spreading Factor (chips): v Code Rate (): Vite Module Parameters Data indicate Time (ms): Baud Rate (bps): AES Cryptography AES Enable (): AES Cryptography Vite EEPROM Factory Reset	pen	Frequency Band	(MHz):		~		
Spreading Factor (chips): vitte Code Rate (): vitte Module Nature (ms): Read Baud Rate (pp): AES Cryptography AES Enable (): AES Cryptography Vitte EEPROM Factory Reset Serial log viewer EEPROM Factory Reset [13:477:11.158] COH33 Serial log viewer AA-31-80-25 [13:477:11.186] COH33	ose	Pandwidth (kHz)			~	Males	1
Spreading Factor (chips): v Code Rate (): v Module Parameters Data Indicate Time (ms): Baud Rate (bps): AES Cryptography AES Enable (): AES Cryptography Virte etadow Serial log viewer EEPROM Factory Reset Said Rate (-9)-60-AI Baud Rate (-9)-60-AI Serial log viewer EEPROM Factory Reset Said Rate (-9)-60-AI Baud Rate (-9)-60-AI		Bandwidth (KH2).	·			white	_
Serial log viewer [13:477:11.186] COMBAR Code Rate (): Module Parameters Data Indicate Time (ms): Baud Rate (lops): AES Cryptography Write		Spreading Factor	(chips):		~		
Module Parameters Data Indicate Time (ms): Baud Rate (bps): AES Enable (): AES Enable (): AES Cryptography Write Factory Reset EEPROM Factory Reset	2 N N N N N N N N N N N N N N N N N N N	Code Rate ():			~		
Serial log viewer [13:47:11.158] COM33 COM33 Com33	W						
Serial log viewer Sata Indicate Time (ms): Baud Rate (bps): AES Cryptography Write Extra log viewer [13:47:11.158] COM33 COM33 COM33 COM33 Baud Rate (bps): AES Cryptography Write EEPROM Factory Reset	Ŭ	Module Parameters					
Baud Rate (bps):	E E E	Data Indicate Tin	ne (ms):			Read	
AES Enable (): AES Cryptography Write Image: Constraint of the second secon		Baud Rate (bps):	7		~		
Serial log viewer EEPROM Factory Reset [13:47:11.186] COM33 COM33 < AA-51-01-98-AB	MIPOIE	AFS Enable ():		AFS Country	ranhv	Write	
Serial log viewer EEPROM Factory Reset [13:47:11.158] COM33 -> AA-31-00-25 [13:47:11.186] COM33 -> AA-31-00-44				Aco crypto	Judpiny	- mile	_
Serial log viewer [13:47:11.158] COM33 -> AA-31-00-25 [13:47:11.186] COM33 <- AA-81-01-00-AN B B B B B B B B B B B B B B B B B B B		Factory Reset	EEPROM	Factory Reset			
	Serial log viewer	-> AA-31-00-25	·	~			

The view that will open is divided in 3 main zones:

1)Serial port control

2)Module control

3)Log of the messages exchanged on the serial port.

In the log, the cyan text is about messages from the pc to the module and are indicated with an arrow pointed right, while the green messages are from the module and have an arrow pointing left.



3.2. Module reset

To start with a known configuration reset the module using the "Factory Reset" button in the "Radio Configuration" tab of the GUI.

adio Configuration	Device Information	AES Configuration	Transmission	Testing
Radio Configuration Physic Parameters				
Power (dBm)		14 dBm	Ŷ	Read
Frequency Band (MHz):	2 - 868.125 MHz	~	
Bandwidth (kHz):		0 - 125 kHz	Ý	Write
Spreading Factor	(chips):	10 - 1024 chips	Ý	
Code Rate ():		1 - 4/5	~	
- Module Parameters Data Indicate Tim	ie (ms):	5		Read
Module Parameters				
Module Parameters Data Indicate Tim Baud Rate (bps):	ie (ms):	5 9600 bps	~	Read
Module Parameters Data Indicate Tim Baud Rate (bps): AES Enable ():	ie (ms):	5 9600 bps AES Cryptog	∽ graphy	Read Write
Module Parameters Data Indicate Tim Baud Rate (bps): AES Enable ():	ie (ms):	5 9600 bps AES Cryptog	v graphy	Read Write

This will configure the module with the default parameters as shown in the next table.

Parameter	Value
Power	14 (dBm)
Frequency Band	2 (868.125 MHz)
Bandwidth	0 (125 kHz)
Spreading Factor (chips)	10 (1024)
Code Rate	1 (4/5)

Parameter	Value
Data Indicate Time	5 (ms)
Baud Rate	0 (9600)
AES enable	0 (disabled)

Before set a parameter, read them with the appropriate button so all the fields are filled with the values configured in the module.



Command example

Reset the module to start with a known configuration of the module with the command FACTORY_RESET_CMD (0x31)

Host: 0xAA, 0x31, 0x00, 0x25 Device:0xAA, 0xB1, 0x01, 0x00, 0xA4

4. Sending and receiving a message

For this operation connect two DevKits and open the GUI for each one.

The radio parameters should be the same on both devices.

Use the "Transmission Testing" tab to send a message.



Write the payload (hex format) in the text box and click "Send mes-sage".

The module will then send a message and signal the completion with an indicate message.

On the GUI opened on the second module, an indication message will contain the transmitted payload.



Command example

Send a message with the TX_MSG_CMD (0x50). For example to send the payload "**0x11, 0x22, 0x33, 0x44**":

Host: 0xAA, 0x50, 0x04, 0x11, 0x22, 0x33, 0x44, 0x58 Device:0xAA, 0xD0, 0x01, 0x00, 0x85

Once the transmission is complete, the module sends TX_MSG_IND (0x52):

Device:0xAA, 0x52, 0x05, 0x00, 0xCF, 0x00, 0x00, 0x00, 0x30

The second module, indicates the reception with the RX_MSG_IND (0x53):

Device:0xAA, 0x53, 0x08, 0x00, 0xF2, 0xFF, 0x09, 0x11, 0x22, 0x33, 0x44, 0x57

5. Using AES ciphering

adio Configuration	Device Information	AES Configuration	Transmission	Testing
Radio Configuration Physical Parameters				
Power (dBm)	1	4 dBm	¥	Read
Frequency Band	MHz): 2	- 868.125 MHz	Ý	
Bandwidth (kHz):	0	- 125 kHz	Ŷ	Write
Spreading Factor	(chips): 1	0 - 1024 chips	Ŷ	
Code Rate ():	1	- 4/5	Ŷ	
Module Parameters				
Module Parameters Data Indicate Tim	ie (ms):	5		Read
Module Parameters Data Indicate Tin Baud Rate (bps):	ie (ms):	5 9600 bps	~	Read
Module Parameters Data Indicate Tim Baud Rate (bps): AES Enable ():	ie (ms):	5 9600 bps AES Cryptor	v graphy	Read

Enable the AES ciphering in the *"Radio Configuration"* tab and write the configuration in both modules.



Radio Configuration	Device Information	AES Configuration	Transmission	Testing
AES Configuration				
Application AES ke	ey (HEX):			
00-11-22-33	-44-55-66-77-88-99-	AA-BB-CC-DD-EE-FF		Write
Initialization Vecto	r (HEX):			
11-22-11-22	2-11-22-11-22-11-22	-11-22-11-22-11-22		Write

Write the AES key and the Initialization Vector on both modules using the "AES Configuration" tab.

From now on, every message sent from the module will be ciphered with this key, and will be decoded correctly only by those modules having the same key and initialization vector.

Since the AES ciphering is a block cipher, the payload will be padded with 0x00 to reach a length that is a multiple of the block length (16 bytes).

Command example

Write the AES key and the Initialization Vector:

For example to use the key "**0x00**, **0x11**, **0x22**, **0x33**, **0x44**, **0x55**, **0x66**, **0x77**, **0x88**, **0x99**, **0xAA**, **0xBB**, **0xCC**, **0xDD**, **0xEE**, **0xFF**" use the SET_AES_KEY_CMD (0x58):

Host: 0xAA, 0x58, 0x10, **0xFF, 0xEE, 0xDD, 0xCC, 0xBB, 0xAA, 0x99, 0x88, 0x77, 0x66, 0x55, 0x44, 0x33, 0x22, 0x11, 0x00**, 0xF6

Device:0xAA, 0xD8, 0x01, 0x00, 0x7D

- To set the initialization vector "0x11, 0x22, 0x11, 0x22, 0x11, 0x22, 0x11, 0x22, 0x11, 0x22, 0x11, 0x22, 0x11, 0x22" use the : SET_IV_CMD (0x59):
- Host: 0xAA, 0x59, 0x10, 0x22, 0x11, 0x25

Device:0xAA, 0xD9, 0x01, 0x00, 0x7C

Enable the cipher writing 1 to the AppEnAES parameter using the EEPROM_WRITE_CMD (0x32):

Host: 0xAA, 0x32, 0x02, 0x07, 0x01, 0x1A Device:0xAA, 0xB2, 0x01, 0x00, 0xA3

The above commands should be issued to all modules in the network.

To send a message, proceed as usual.



Host: 0xAA, 0x50, 0x04, 0x11, 0x22, 0x33, 0x44, 0x58 Device:0xAA, 0xD0, 0x01, 0x00, 0x85

Once the transmission is complete, the module sends TX_MSG_IND (0x52):

Device:0xAA, 0x52, 0x05, 0x00, 0x21, 0x01, 0x00, 0x00, 0xDD

The second module, indicates the reception with the RX_MSG_IND (0x53):

Device:0xAA, 0x53, 0x14, 0x00, 0xEE, 0xFF, 0x09, 0x11, 0x22, 0x33, 0x44, 0x00, 0x00,

Contrary to the previous case, now the receiver shows the payload with the padding included.

6. Revision History

Revision	Date	Description	
0.1	11.11.2022	First version	
0.2	22.11.2022	11.2022 Change image and product code in the title	
0.3	06.12.2022	Change the image on the first page Change the name of the document to "User Guide"	